Boxchip -----Multimode network radio world leader in network radio systems



Connected! BOXCHIP OMB Security Channel ...I IMAGE

DMR



About Us

Professional radio manufacturers are sometimes not the best at designing Network Radios.

but then not all makers of Network Radios are the best at producing professional two-way radios!

Introducing Boxchip.

We have more than 10 years professional experience in communications.

We know the cellphone network has weak signal areas; we know that Digital Mobile Radio (DMR) networks can't do the kind of image and video messaging that mobile phones can.

So Boxchip produces devices which seamlessly switch between the phone network and DMR with the best coverage available, wherever you are in the world

With Boxchip, you can'Stay Connected', wherever you are!

Available worldwide via our distribution network.



Boxchip S900A+ LTE+DMR multimode radio -----Stay Connected







| 00A+ Key Features: | |
|--------------------|--|
| Processor | CPU 1.5GHz |
| Android | Android 9.0+ |
| Memory | 2GB /16GB |
| LCD size | 4.0inch,800*480 Pixels |
| LCD touch feature | Web touch/ golve touch/ solar visibility |
| Camera | 8MP+ 5MP camera;Optional 13MP+8MP |
| Gateway mode | Support |
| ROIP | Support |
| VOLTE | Support |
| SIM card | Support dual nano sim |
| Encryption | Support AES256/ AES128/ ARC4 |
| Other features | Bluetooth, Wifi, hotspot, NFC, GPS |



MAIN SEPCIFICATION

| 1.5G | |
|---|--|
| | |
| Android 9.0+ | |
| 2GB+16GB | |
| 4.0inch TFT IPS,400*480 Pixels,gorillia III | |
| 1 B2 B5 B8 | |
| 81 B3 B5 B7 B8 B20 B26 B28A B28B(EU version) | |
| 32 B4 B5 B7 B12 B13 B17 B26 B28A B28B(US version) | |
| 338 B39 B40 B41 | |
| Oual cameras 5MP & 8MP @30fps (Video mode) | |
| 2.4G /5.8G | |
| Dual BT v4.1 | |
| GPS, A-GPS,Glonass | |
| ⊅36,2W | |
| /es | |
| ype-C,M6 | |
| p65 | |
| 4500mAh | |
| | |

DMR SPECIFICATION

| Frequency Band | UHF: 400-480MHz or VHF: 136-174MHz |
|---------------------------|---|
| Channel | 1000 or customize |
| Channel Spacing | 12.5KHz/25KHz |
| Tx Power | 1W/2W |
| Rxsensitivity | Analog: 121dBm/12dbSINAD(Rated) Digital: 117dBm/BER1% |
| Inter-modulation | ≥65dB |
| Blocking | ≥84dB |
| Spurious of Suppression | ≥70dB |
| Response | ≥70dB |
| Neighbor hood selectivity | ≥60dB |
| Frequency stability | ±0.5ppm |
| Antenna Impedance | 50Ω characteristic impedance |
| Audio Output | 1W(Rated) |
| Audio Distortion | ≤3% |
| Encryption | ARC4/AES128/AES256 |

ACCESSORIES

| STAN | IDARD | OPTIONAL |
|-------------|-------|--|
| USB Cable | 1 pcs | Earbud Base set with PTT button and microphone |
| Charger | 1 pcs | Remote Micro Speaker |
| Back Clip | 1 pcs | PTT earphone with external camera |
| Antenna | 1 pcs | Dock charger |
| User Manual | 1 pcs | Charger station |



BOXCHIP RADIO HAVE BEEN USED IN VARIOUS OF APPLICATION SCENARIOS









Office: +86-755-88848348 E-mail: info@boxchiptt.com http://www.boxchiptt.com





